

A-3200D Series

Digital Mixer Amplifier


A-3200D is a **high-performance digital mixer amplifier series** coming in different set-ups and the ideal choice **for paging and background music**. The series divides into four different sub-series: **A-3200DM, A-3200DZ, A-3200DMZ and A-3200DME**. All of these offer the choice of 3 rated outputs: 120 W, 240 W and 480 W (A-3200DME only 480 W). If required, both low-impedance and high-impedance speakers can be connected. Regardless of the scale of your project, these options ensure that there is a suitable match for your needs. The distinguishing features among the sub-series are:

- A-3200DZ: Zone management
- A-3200DM: Media player
- A-3200DMZ: Media player with zone management
- A-3200DME: Media player with 5-band equalizer

Due to its digital technology, this mixer amplifier series is **energy efficient and eco-friendly**, saving costs at an optimal price/performance ratio.

A-3200DZ / A-3200DMZ

Multi-zone management required? With the **A-3200DZ**, **up to five zones** can be managed in one amplifier. The device offers connections for **up to 4 microphones** and **2 additional AUX inputs**. Additional **media player** required? The **A-3200DMZ** also has an integrated media player with the following interfaces: Bluetooth / USB / SD card / FM radio. These mixing amplifiers with zone management offer full sound control and flexible output power.



A-3200DME-EB

The **A-3200DME** offers that certain extra for all audio lovers who like to enjoy good sound: using the **equalizer**, **five different frequencies** (80, 315, 1000, 3150 and 8000 Hz) can be set and thus raise the sound experience to a higher level. The integrated media player including **Bluetooth function** allows flexible connection, ideal for frequently changing users.



Application examples

The A-3200D series for paging and background music in:

- Schools
- Houses of worship
- Offices
- Large shops
- Restaurants
- Gyms
- Mid-size halls
- Conference



A-3200D Series

Digital amplifier series

Features



	A-3200DM	A-3200DZ	A-3200DMZ	A-3200DME
Flexible power output (120, 240, 480) W	✓	✓	✓	Only 480 W
Master and Input volume control	✓	✓	✓	✓
Volume control for MIC 4/AUX1 Level adjust depending on selected input	✓	✓	✓	✗
Phantom power for condenser microphone/ option for chime microphone	✓	✓	✓	✓
MIC 1 priority input	✓	✓	✓	✓
Impedance selector	4Ω or 83Ω	4Ω or 83Ω	4Ω or 83Ω	4Ω or 83Ω
Bass and treble control	✓	✓	✓	✗
5 Band equalizer 5 knobs to control the gain of different frequencies (80, 315, 1000, 3150, 8000 Hz)	✗	✗	✗	✓
Inputs				
MIC	4	4	4	5
AUX	2	2	2	2
Media Player LED Display, USB, SD/MMC Card, Bluetooth, Radio FM, Record	✓	✗	✓	✓
Outputs				
Speaker screw terminal	✓	✓	✓	✓
Direct line	✓	✓	✓	✓
Rec out	✓	✓	✓	✓
Flexible speaker-out zone management Zone selector terminal	✗	✓	✓	✗

Specifications A-3200D series

Frequency Response:	50 – 20000 Hz
S/N Ratio:	Over 60 dB
Dimensions:	420 (W) x 100.9 (H) x 357 (D) mm
Weight:	5.0 kg
Finish:	Panel: ABS Resin, black
	Case: Steel Plate, black
Accessory:	1x Antenna FM radio (1 m)

More informations
on our Website:



TOA Electronics Europe GmbH

Specifications are subject to change without notice. 04|2024

www.toa.eu